

# SANGEAN

A World of Listening

## PR-D4

**FM / AM DIGITAL TUNING  
PORTABLE RECEIVER**



- \* PLL Synthesized tuning system.
- \* 10 memory presets ( FM5, AM5 ).
- \* Rotary volume control.
- \* LCD displays separately clock and radio information.
- \* Auto scan stations.
- \* Two alarm timers ( radio and buzzer ).
- \* Snooze.
- \* Sleep ( auto shut off ).
- \* Battery power status indication.
- \* 3 inches full range speaker.
- \* Long lasting battery operation.
- \* DC 6 V jack.
- \* Headphones jack.

*See over page for technical specifications.*

**CANOHM**

3/200 Turner Street Port Melbourne VIC 3207

Ph: 03 9645 4700 ★ Fx: 03 9646 7366 ★ Email: sales@canohm.com.au

Website: www.canohm.com.au

# SANGEAN



## ► MODEL

## PR-D4

<b>TUNING</b>	Type	PLL synthesizer
	Memory Presets	10 / 15 (Option)
	Rotary Tuning	
	Auto Tuning System	
<b>DISPLAY</b>	Type	LCD
	Size (mm)	99.6 x 24.6
	Back light	Yes
<b>BAND FM</b>	Frequency MHz	87.5-108 / 76-90 CH1,2,3
	Stereo	
	RDS	
<b>MW</b>	Frequency kHz	520-1710 / 522-1629
<b>CLOCK</b>	Real time	Yes
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	Yes
	Sleep	Yes
<b>OUTPUT</b>	Speaker unit	3 inch 4 ohm
	Buzzer	
<b>OUTPUT POWER BY</b>	AC/DC IN (Speaker)	
	Batteries (Speaker)	700 mW
	Earphones	5+5 mW
<b>POWER SUPPLY</b>	DC IN	6 V DC 400 mA
	Batteries (Main power)	4 x 1.5 V (UM-1)
<b>I/O SOCKET</b>	DC in	Yes
	AC in	
	Earphones	Yes
<b>ACCESSORIES</b>	AC Adapter	Yes (with PR-D4AD version)
<b>DIMENSIONS</b>	WxHxD (mm)	237 x 148 x 62
	Weight (g)	840