

SANGEAN

A World of Listening

PR-D7

FM/AM DIGITAL TUNING
PORTABLE RECEIVER

Rechargeable



\$169.00 RRP

AUD\$ inclusive of GST

- ★ Available in black or white
- ★ FM/AM digital tuner with 10 (2 x 5) presets
- ★ Automatic station search
- ★ Ultra compact, good for travelling
- ★ Plays on rechargeable* and dry-cell batteries
- ★ Back light LCD
- ★ Rotary control for volume
- ★ Clock
- ★ Charge indicator
- ★ Snooze and sleep timer
- ★ Radio alarm
- ★ Humane Waking System buzzer alarm
- ★ Stereo earphone connection
- ★ Telescopic antenna
- ★ Includes AC adaptor

* Not included. See over page for technical specifications.

CANOHM

3/200 Turner Street Port Melbourne VIC 3207

Ph: 03 9645 4700 ★ Fx: 03 9646 7366 ★ Email: sales@canohm.com.au

Website: www.canohm.com.au

SANGEAN



► MODEL

PR-D7

TUNING	Type	PLL synthesizer
	Memory Presets	10
DISPLAY	Type	LCD
	Size (mm)	81 x 21
	Back Light	Yes
BAND FM	Frequency MHz	87.5 - 108 / 76 - 90 CH1, 2, 3
MW	Frequency kHz	520 - 1710 / 522 - 1629
CLOCK	Real Time	Yes
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	Yes
	Sleep	Yes
OUTPUT	Speaker Unit	2.5 inch 8 Ohm
POWER BY	AC/DC IN (Speaker)	1.6 W (DC IN)
	Batteries (Speaker)	600 mW (Ni-HM 7.2 V)
	Earphones	5+5 mW
POWER SUPPLY	DC IN	12 V DC 500 mA
	Batteries (Main power)	6 x 1.5 V (UM-3)
CHARGE . BT	Charge BT	6 x 1.2 V (UM-3)
I/O SOCKET	DC in	Yes
	Earphones	Yes
ACCESSORIES	AC Adaptor	Yes
DIMENSIONS	WxHxD (mm)	215 x 116 x 40
	Weight (g)	574